



- "RELAYS"**
- | INDEX | NO | COIL | TYPE | CONTACTS | USE |
|-------|----|--------|-----------|----------|---------------------------------|
| 3E | A | R20-4 | AG | 4A | SELECTION SEQUENCE RELAY |
| 2E | C | R20-4 | AG | 4A | RED POP BUMPER RELAY |
| 2E | E | R20-4 | AG | 3A, 1B | WHITE POP BUMPER RELAY |
| 4E | F | R20-5 | MAG | 2A, 2C | RED POP BUMPER CONTROL RELAY |
| 4E | G | R20-5 | MAG | 2A, 2C | YELLOW POP BUMPER CONTROL RELAY |
| 7E | H | R20-4 | AG | 3A | 50 POINT RELAY |
| 2E | K | R20-4 | AG | 4A | YELLOW POP BUMPER RELAY |
| 10E | L | A-3891 | INTERLOCK | 1B | SEQUENCE SCORING CONTROL RELAY |
| 12E | LR | A-3891 | AG | 4A | 10 POINT RELAY |
| 5E | M | R20-4 | AG | 4A | 1 POINT RELAY |
| 7E | N | R20-4 | AG | 4A | 100 POINT RELAY |
| 5E | Q | R20-4 | AG | 5A | 115 V. HOLD RELAY |
| 13E | R | A-3498 | MAG. | 1A | TARGET RELAY |
| 7E | X | R20-4 | AG | 5A | SPIN RELAY |
| 7E | Z | R20-4 | AG | 4A, 1B | SPIN RELAY |
| 3E | 1R | A-3891 | INTERLOCK | 3A, 1B | #1 SELECTION RELAY |
| 3E | 2 | A-3891 | INTERLOCK | 3A, 1B | #2 SELECTION RELAY |
| 11E | 2R | A-3891 | INTERLOCK | 3A, 1B | #3 SELECTION RELAY |
| 3E | 3 | A-3891 | INTERLOCK | 3A, 1B | #4 SELECTION RELAY |
| 11E | 4R | A-3891 | INTERLOCK | 3A, 1B | #5 SELECTION RELAY |
| 3E | 5 | A-3891 | INTERLOCK | 3A, 1B | #5 SELECTION RELAY |

- "BANK"**
- | INDEX | NO | COIL | CONTACTS | USE |
|-------|----|--------|------------|-------------|
| BE | T | A-1118 | 1A, 1B, 1C | TILT RELAY |
| 12E | D | A-1118 | 3A, 2B, 1C | RESET RELAY |
| 13E | S | A-1856 | 6A, 2C | START RELAY |

- "OTHER COILS USED"**
- UNITS, TENS, HUNDREDS & THOUSANDS UNIT DRIVE COILS (A-5193)
 - BALLS TO PLAY UNIT DRIVE COIL (A-1496)
 - SUBTRACT COIL (A-5194)
 - ROTO UNIT DRIVE COIL (A-5197)
 - KNOCKER COIL (A-5143)
 - UNITS BELL COIL (A-5143)
 - TENS BELL COIL (A-5143)
 - HUNDREDS BELL COIL (A-5143)
 - POP BUMPER COILS (A-4893)
 - FLIPPER COILS (A-5141)
 - KICKING RUBBER COILS (A-5194)
 - BALL RELEASE COIL (A-5195)
 - BANK SETUP COIL (A-5197)
 - MOTOR NO. 116
 - LIGHTBOX BALL SHOOTER COIL (A-1496)

- "WORD ABBREVIATIONS"**
- R.O. = ROLLOVER
 - POS. = POSITION
 - SW. = SWITCH
 - SUBT. = SUBTRACT
 - ADJ. = ADJUSTABLE

- "COLOR CODE ABBREVIATIONS"**
- BL - BLUE
 - BR - BROWN
 - BLK - BLACK
 - GR - GREEN
 - OR - ORANGE
 - PUR - PURPLE
 - SL - SLATE
 - WH - WHITE
 - WH-MAR - MAROON
 - PUR - PURPLE



MOTOR SWITCH POSITIONS

POSITION	A	B	C	D	E
#1	3A	1B	1A-2B	1A	
#2		1B	2A	1B-1C	
#3		BRANKE			
#4				1B-1C	

Reproduced under license from Gottlieb Development LLC. P.O. Box 8369, Pelham, NY 10803 USA, owner of the Gottlieb® and D. Gottlieb & Co.® trademarks and related copyrights, by Steve Young, The Pinball Resource & Commerce Street, Poughkeepsie, NY 12603 USA. No further reproduction permitted.

OPERATOR PLEASE NOTE:
THE PURPOSE OF ALL THE ADJUSTMENTS ON THIS GAME ARE TWOFOLD: FIRST THAT THE PLAYER RECEIVES THE PROPER AMOUNT OF AMUSEMENT FOR THE COIN INSERTED, AND SECOND THAT THE OPERATOR RECEIVES A FAIR RETURN ON HIS INVESTMENT.

FLIPPER PARADE

