
ABBREVIATIONS
ADJ. ADJUSTMENT
M-B MUSHROOM BUMPER
POS. POSITION
RE. RELAY
SCM. SCORE MOTOR
SOL. SOLENOID
T-B THUMPER BUMPER
CABINET TO INSERT PLUGS
PANEL TO CABINET PLUGS
FLIPPER PLUG
DOOR PLUG
WIRES ENCLOSED IN INDICATES FULL GAUGE WIRE USED AT POSITION ON PLUGS.
COIL LOCATING CHART
NAME OF COIL LOCATION
BALL COUNT UNIT RESET SOL. F-20
BALL COUNT UNIT STEP UP SOL. F-19
BALL INDEX RE. F-8
COIN LOCKOUT COIL F-1
COIN RE. F-2
CREDIT RESET SOL. F-23
CREDIT UNIT RESET SOL. F-23
CREDIT UNIT STEP UP SOL. F-11
EL TOBO TRIP RE. F-4
EL TOBO TRIP SOL. F-4
EXTRA BALL RE. F-14
GAME OVER TRIP RE. F-13
GREEN T-B LITE RE. F-14
KNOCKER SOL. F-21
LEFT FLIPPER SOL. F-18
LEFT SLING SHOT SOL. F-16
LEFT SLINGSHOT SOL. F-17
L. TRIP RE. F-10
L. TRIP SOL. F-10
OUTHOLE KICKER SOL. F-21
OUTHOLE RE. F-7
RESET RE. F-21
RIGHT FLIPPER T-B RE. F-15
RIGHT GREEN T-B RE. F-15
RIGHT SLING T-B SOL. F-20
R. TRIP RE. F-9
R. TRIP SOL. F-9
SCORE RESET RE. F-21
TILT TRIP RE. F-22
TOTAL PLAY MOTOR F-23
TOTAL RE. F-23
YELLOW T-B RE. F-17
YELLOW T-B SOL. F-20
10-100 UNIT STEP UP SOL. F-12
#1 M-B RE. F-18
#2 M-B RE. F-18
#3 M-B RE. F-18
741 "E" TRIP RE. F-3
741 "E" TRIP SOL. F-3
1 ROLL OVER LITE RE. F-24
2 ROLL OVER LITE RE. F-24
3 ROLL OVER LITE RE. F-25
1 COIN UNIT STEP UP SOL. F-2
2nd COIN CHUTE RE. F-4
3rd COIN CHUTE SOL. F-5
500 POINT CAVE SOL. F-20
750 POINT CAVE SOL. F-20
1000 POINT CAVE SOL. F-20
10 POINT RE. F-17
100 POINT RE. F-17
1000 POINT RE. F-17
10-900 UNIT STEP UP SOL. F-15
100-900 UNIT STEP UP SOL. F-15
100-900-1000 UNIT STEP UP SOL. F-16
10-200-90-2000 UNIT STEP UP SOL. F-17
SWITCH SYMBOLS
NORMALLY OPEN SWITCH (CLOSED WHEN ENERGIZED)
NORMALLY CLOSED (OPEN WHEN ENERGIZED)
MAKE & BREAK SWITCH
SCORE MOTOR OPERATED SWITCH
WIRE COLOR CODE
SEQUENCE OF OPERATION OF SCORE MOTOR SWITCHES
POSITIONS
TRANSFORMER WIRING FOR 230/240 V. 50/60 CY. INPUT
TRANSFORMER WIRING FOR 115 V. 50/60 CY. INPUT
FOR 220 V. OR 240 V. INPUT TIE LUG 1 AND LUG 3 TOGETHER LEAVE 1 WIRE ON LUG 1
LUG 5 (115 V.) TAP
FOR 240 V. ONE SIDE OF LINE CORD ON LUG 7
ONE SIDE OF LINE CORD ON LUG 5
FOR 115 V. INPUT TIE LUG 1, LUG 2 AND LUG 3 TOGETHER LEAVE 1 AND LUG 2 TOGETHER
70-1P (ORANGE) WIRE ON LUG 1
NOT USED
EL TORO
907
1 PLAYER
W-1042-101
4-25-72
Bally
MANUFACTURING CORP.
2640 W. BELMONT AVE.
CHICAGO, ILL. 60618