

Sol. No	Solenoid description	Solenoid Type	Wire Color	Connector	Driver Transistor	Solenoid Coil Type
1	Left Slingshot	Momentary	Pur-Wht	A3J2-9, J1-2	Q1	J-27-1700
2	Right Slingshot	Momentary	Brn	A3J2-4, J1-3	Q2	J-27-1700
3	Knocker	Momentary	Blk-Yel	A3J2-5, J3-4	Q3	N-26-1200
4	Lower Right Thumper	Momentary	Brn-Yel	A3J1-5	Q4	J-26-1200
5	Top Thumper	Momentary	Grn-Red	A3J2-10	Q5	J-26-1200
6	4-Bank Drop Target Reset	Momentary	Gry	A3J2-11	Q6	B-27-2300
7	Ball Kicker	Momentary	Yel-Red	A3J2-12	Q7	J-28-2300
8	Saucer	Momentary	Blk-Yel	A3J5-10	Q8	J-28-2300
9	Outhole	Momentary	Orn-Red	A3J5-9	Q9	J-26-1000
10	Lower Left Thumper	Momentary	Blk-Blu	A3J5-15	Q10	J-26-1200
11	Drop Target (Black Star)	Momentary	Yel-Blu	A3J5-14	Q11	C1-34-3400
12	Drop Target (Yellow Star)	Momentary	Orn-Wht	A3J5-13	Q12	C1-34-3400
13	Drop Target (Red Star)	Momentary	Orn-Blk	A3J5-12	Q13	C1-34-3400
14	Drop Target (Blue Star)	Momentary	Blk	A3J5-11	Q14	C1-34-3400
15	Flipper enabling relay	Continuous	--	--	Q15	48V Relay
16		Momentary		A3J5-8, J2-6, J3-7,	Q16	
17	G.I. Relay	Continuous	Wht-Blu	A3J5-7	Q17	48V Relay
18		Continuous		A3J5-3, J2-15, J3-9	Q18	
19	Coin Lockout	Continuous	Yel-Wht	A3J2-8	Q19	C-36-5300
Flipper Circuits		Power Wire	Flipper Coil Wire	Flipper Button Wire		Coil
	Left Flipper	Blu-Wht	Grn A3J1-8	Blu A3J2-2		J-25-450/34-4500
	Right Flipper	Blu-Wht	Orn A3J1-9	Red A3J2-1		J-25-450/34-4500