

A = NO
 B = NC
 C = M/B

"RELAYS"

INDEX NO	COIL	TYPE	CONTACTS	USE
4E	A R20-5	MAG.	5C	ALTERNATING RELAY
15E	B R20-4	MAG.	5A,2B	CHANGE PLAYERS & ADD BALLS PLAYED RELAY
2E	C R20-4	MAG.	3A	YELLOW POP BUMPER RELAY
6E	D R20-4	MAG.	6A,1B	RESET RELAY
8I	E R20-6	MAG.	3A	REPLAY BUTTON RELAY
2E	G R20-4	MAG.	3A	RED POP BUMPER RELAY
12E	H A-3498	MAG.	1A,2B,1C	30Y. HOLD RELAY
4E	I R20-4	"R"	3A,1B	RED TARGET RELAY
4E	J R20-4	"R"	3A,1B	YELLOW TARGET RELAY
18I	K R20-6	MAG.	6A	COIN CHUTE RELAY
6E	M R20-4	"R"	4A	10 POINT RELAY
7E	N R20-4	"R"	4A	1 POINT RELAY
14E	O R20-5	MAG.	1A,1B,4C	1ST & 2ND PLAYER SCORING CONTROL RELAY
14E	P R20-5	MAG.	1A,1B,4C	1ST & 2ND PLAYER SCORING CONTROL RELAY
8E	Q R20-4	"R"	4A	100 POINT RELAY
16E	R A-3498	MAG.	1C	115 V. HOLD RELAY
5E	S R20-4	MAG.	3A	50 POINT RELAY
12E	T A-1084	MAG.	1B	TILT RELAY
5E	U R20-4	MAG.	4A	10 TIMES TARGET VALUE RELAY
2E	V R20-5	MAG.	3A,2C	GREEN POP BUMPER CONTROL RELAY
18I	W R20-6	MAG.	3A,2B,1C	EXTRA CHUTE RELAY
3E	X R20-4	MAG.	3A	TOP GREEN POP BUMPER RELAY
3E	Y R20-4	MAG.	3A	BOTTOM GREEN POP BUMPER RELAY
2E	Z R20-4	MAG.	3A	WHITE POP BUMPER RELAY

"BANK"

INDEX NO	COIL	CONTACTS	USE
4E	4B A-1118	2A,1B	2ND PLAYER THOUSANDS RELAY
4E	3B A-1118	2A,1B	1ST PLAYER THOUSANDS RELAY
16E	2B A-1118	2A,1B	2ND PLAYER MATCH RELAY
16E	1B A-1118	1A,1B	1ST PLAYER MATCH RELAY
12E	TB ₁ A-1118	1A,3B,1C	1ST PLAYER TILT RELAY
12E	TB ₂ A-1118	2A,3B,1C	2ND PLAYER TILT RELAY
9E	PB A-1118	3A,3B	2ND PLAYER RELAY
8E	ZB A-1118	2A,1B	1ST BALL RELAY
8E	QB A-1118	1A,2B	GAME OVER RELAY
14E	SB A-1118	2A,1B,2C	START RELAY
8E	XB A-1118	2A,2B	LAST BALL RELAY

"OTHER COILS USED"

REPLAY UNIT DRIVE COIL (A-1496)
 2ND STEP DRIVE COIL (A-5197)
 SUBTRACT COIL (A-5194)
 UNITS, TENS & HUNDREDS UNIT DRIVE COILS (A-5193)
 BALLS PLAYED UNIT DRIVE COIL (A-496)
 RESET COIL (A-5194)
 0-9 UNIT DRIVE COIL (A-1496)
 RED TARGET VALUE UNIT DRIVE COIL (A-1496)
 YELLOW TARGET VALUE UNIT DRIVE COIL (A-1496)
 KNOCKER COIL (A-5143)
 UNITS BELL COIL (A-5143)
 TENS BELL COIL (A-5143)
 HUNDREDS BELL COIL (A-5143)
 POP BUMPER COILS (A-4893)
 BOTTOM FLIPPER COILS (A-5141)
 TOP FLIPPER COILS (A-5194)
 BALL RELEASE COIL (A-5195)
 KICKING RUBBER COILS (A-5194)
 BANK SETUP COIL (A-5196)
 MOTOR NO 116

"WORD ABBREVIATIONS"

R. O. - ROLLOVER
 POS. - POSITION
 SW. - SWITCH
 SUBST. - SUBTRACT
 ADJ. - ADJUSTABLE
 SPEC. - SPECIAL
 SEQ. - SEQUENCE

"COLOR CODE ABBREVIATIONS"

BL. - BLUE SL. - SLATE