

Jetsons Solenoid List

| SOL # | FUNCTION | WIRE COLOR | DRIVER | COIL # | BANK # | FUSE |
|-------|---------------------------|---------------|--------|------------|--------|-----------|
| 0 | Knocker (optional) | | SOL0 | 23-800 | 0 | F1 3A Slo |
| 1 | Shaker Motor (optional) | | SOL1 | | 0 | F1 3A Slo |
| 2 | Right Flipper Low | Orange-Green | SOL2 | FL-11629 | 0 | F1 3A Slo |
| 3 | Right Flipper High Center | Orange-Violet | SOL3 | FL-11629 | 0 | F1 3A Slo |
| 4 | Ball Trough Load | Orange-Black | SOL4 | 26-1200 | 0 | F1 3A Slo |
| 5 | Ball Launch | Orange-Gray | SOL5 | 23-800 | 0 | F1 3A Slo |
| 6 | Left Flipper High Center | Orange-White | SOL6 | FL-11629 | 0 | F1 3A Slo |
| 7 | Left Flipper Low | Orange-Blue | SOL7 | FL-11629 | 0 | F1 3A Slo |
| 8 | Scoop | Blue-Green | SOL8 | 23-800 | 1 | F2 3A Slo |
| 9 | Left Slingshot | Blue-Red | SOL9 | 23-800 | 1 | F2 3A Slo |
| 10 | Right Slingshot | Blue-Gray | SOL10 | 23-800 | 1 | F2 3A Slo |
| 11 | Not Used | Not Used | SOL11 | Not Used | 1 | F2 3A Slo |
| 12 | Not Used | Not Used | SOL12 | Not Used | 1 | F2 3A Slo |
| 13 | Not Used | Not Used | SOL13 | Not Used | 1 | F2 3A Slo |
| 14 | Not Used | Not Used | SOL14 | Not Used | 1 | F2 3A Slo |
| 15 | Not Used | Not Used | SOL15 | Not Used | 1 | F2 3A Slo |
| 16 | Up Post | Violet-Black | SOL16 | AE-27-1200 | 2 | F3 3A Slo |
| 17 | Lower Pop Bumper | Violet-Green | SOL17 | 23-800 | 2 | F3 3A Slo |
| 18 | Left Pop Bumper | Violet-White | SOL18 | 23-800 | 2 | F3 3A Slo |
| 19 | Saucer Kick Out | Violet-Red | SOL19 | 23-800 | 2 | F3 3A Slo |
| 20 | Right Pop Bumper | Violet-Gray | SOL20 | 23-800 | 2 | F3 3A Slo |
| 21 | Not Used | Not Used | SOL21 | Not Used | 2 | F3 3A Slo |
| 22 | Not Used | Not Used | SOL22 | Not Used | 2 | F3 3A Slo |
| 23 | Not Used | Not Used | SOL23 | Not Used | 2 | F3 3A Slo |

Driver Transistors IRL540

Feb. 11, 2019 Ken Layton