

Sol. No	Solenoid description	Solenoid Type	Wire Code	Wire Color	Connector	Driver Transistor	Solenoid Coil Type	selftest	PinMame	transistor
1	Outhole Kicker	Momentary	95	Gry-Wht	A3J1-5	Q4	AN-26-1200	1	7	Q4
2	Knocker	Momentary	85	Blk-Wht	A3J3-4, J2-5	Q3	AR-26-1200	2	6	Q3
3	Saucer	Momentary	40	Grn	A3J5-10	Q8	AO-27-1300	3	8	Q8
4	Chime 10	Momentary	81	Blk-Red	A3J2-4, J1-3	Q2	CN-31-2000	4	1	Q2
5	Chime 100	Momentary	81	Blk-Red	A3J2-9, J1-2	Q1	CN-31-2000	5	2	Q1
6	Chime 1000	Momentary	67	Brn-Orn	A3J2-10	Q5	CN-31-2000	6	3	Q5
7	Chime Extra	Momentary	74	Orn-Grn	A3J2-11	Q6	CN-31-2000	7	4	Q6
8	Left Thumper Bumper	Momentary	71	Orn-Red	A3J5-9	Q9	AN-26-1200	8	11	Q9
9	Right Thumper Bumper	Momentary	85	Blk-Wht	A3J5-15	Q10	AN-26-1200	9	12	Q10
10	Bottom Thumper Bumper	Momentary	80	Blk	A3J5-13	Q12	AN-26-1200	10	13	Q12
11	Left Slingshot	Momentary	18	Red-Blk	A3J5-14	Q11	AN-26-1200	11	15	Q16
12	Right Slingshot	Momentary	83	Blk-Yel	A3J5-8, J2-6, J3-7,	Q16	AN-26-1200	12	14	Q11
13	Left Drop Target Reset	Momentary	65	Brn-Wht	A3J5-12	Q13	NO-26-2300	13	9	Q13
14	Right Drop Target Reset	Momentary	70	Orn	A3J5-11	Q14	NO-26-2300	14	10	Q14
15	Coin Lockout	Continuous	36	Yel-Brn	A3J2-8	Q19	FO-36-7000	15	18	Q19
16	Flipper enabling relay	Continuous	--	--	--	Q15	48V Relay	16	19	Q15
		Momentary	81	Blk-Red	A3J2-12	Q7				
		Continuous	67	Brn-Orn	A3J5-7	Q17				
		Continuous	81	Blk-Red	A3J5-3, J2-15, J3-9	Q18				
Flipper Circuits		Power Wire	Flipper Coil Wire		Flipper Button Wire		Coil			
	Left Flipper	60 (Brn)	40 (Grn)	A3J1-8	20 (Blu)	A3J2-2	AQ-25-500/34-5050			
	Right Flipper	60 (Brn)	70 (Orn)	A3J1-9	10 (Red)	A3J2-1	AQ-25-500/34-5050			